

microlab

just listen

M-700U High Fidelity multimedia system 2.1 subwoofer speakers for full range sound

Features:

- Power 2.1 subwoofer system for multimedia performances
- Ideal for digital movies, TV, CD/DVD and Mp3/Mp4 playbacks
- Front control and digital media interfaces
- Wireless remote control for easy convenient adjustment
- Satellites with crystal clear tweeter drivers
- Reflex tunnel design for efficient bass driver, deeper bass and depth
- Comes with multi-input interfaces for various playback modes such as USB dongle and SD card, 3.5mm and 2RCA jacks
- FM radio tuner with telescopic antenna



Specifications:

Amplifier specs

- Output power: 46 Watt RMS
- Power distribution: 14 Watt x 2 + 18 Watt
- Harmonic distortion: < 0.3% 1 W 1 kHz
- Frequency response: 35 Hz - 20 kHz
- Signal/Noise ratio: > 75 dB
- Separation: > 45 dB
- FM radio: 87.0 MHz to 108 MHz frequency range

Speakers:

- Tweeter driver type: 2.5" x 2
- Tweeter rated power: 15 Watt x 2 4 ohm
- Subwoofer driver type: 5"
- Subwoofer rated power: 20 Watt 6 ohm

Interfaces:

- Output: RCA
- Input: 3.5mm stereo , RCA
- Multimedia: USB type A, SD card reader

Power:

- AC power: AC 220 V - 240 V, 50 Hz 200 mA or 120 V, 60 Hz 400 mA

Package contents:

- M-700U subwoofer
- M-700U satellites x 2
- 3.5 mm stereo to 2RCA cable
- Infrared remote control
- User manual

Dimensions

- Subwoofer: 165 x 290 x 240 mm (L x H x D)
- Satellites: 90 x 75 x 180 mm (L x H x D)
- Product net weight: 3.7 kg
- Giftbox dimension: 343 x 208 x 358 mm (L x W x H)
- Giftbox Net weight: 8 kg
- Export carton box dimension: 431 x 355 x 736 mm (L x W x H)
- Export carton gross weight: 18.8 kg

Warranty Notice: *1 Year Warranty

Microlab Electronics Company Limited

Baozi South Road, Microlab Industrial Park, Shenzhen Grand Industrial Zone, Longgang District, Shenzhen, China 518122
Tel: +86 755 86243211 Fax: +86 755 28290000
Email: jennifersheng@microlab.cn

EAN: 694519885146 8

Ver: 2.0



Product image, Terms and Specifications are subject to changes without further notice

© 2011 Microlab Electronics Co., Ltd